

Claims

We claim:

- 1 1. A method for shaping a spectrum of an impulse radio signal, comprising:
2 generating a set of basis pulses at a plurality of frequencies and a
3 plurality of random delays;
4 weighting the set of basis pulses by weights;
5 delaying the set of basis pulses by delays; and
6 combining linearly the weighted and delayed basis pulses to conform
7 the spectrum to a spectral mask.
- 1 2. A method of claim 1 further comprising:
2 shifting frequencies of the weighted and delayed basis pulses before
3 the combining.
- 1 3. The method of claim 1 wherein the weights and delays are fixed over time
2 for a predetermined spectral mask.
- 1 4. The method of claim 1 wherein the weights and delays vary over time to
2 adaptively shape the spectrum.
- 1 5. The method of claim 1 wherein the basis pulses are Gaussian in form.
- 1 6. The method of claim 1 wherein the weighting and delaying are performed
2 by a set of filters and a set of delay lines, and the combining is performed by
3 an adder.

1 7. The method of claim 1 further comprising:

2 evaluating a cost function to determine the weights and delays.

1 8. The method of claim 7 wherein the cost function, f , includes first and
2 second functions f_1 and f_2 , and

3 $f(\underline{p}(t), S) = \alpha f_1(\underline{p}(t)) + \beta \sum_{M(\Omega) \in S} f_2(\underline{p}(t), M(\Omega))$, where α and β are

4 predetermined constants, $S = M(\Omega)$ denote the spectral mask, and $\underline{p}(t)$
5 denotes the set of basis pulses, and the first function f_1 models a cost of
6 generating the basis pulses, and the second function f_2 models an
7 approximation error.

1 9. The method of claim 1 wherein the delays are fixed, and further
2 comprising:

3 solving a quadratic optimization problem to approximately minimize a
4 deviation from the spectral mask.

1 10. The method of claim 9 further comprising:

2 refining the weights and delays by a non-linear optimization.

1 11. The method of claim 10 wherein the non-linear optimization is
2 performed by a back-propagation neural network.

1 12. The method of claim 10 wherein the non-linear optimization is
2 performed by a multiple-layer neural network

- 1 13. The method of claim 10 wherein the non-linear optimization is
2 performed by a simulated annealing process.
- 1 14. The method of claim 1 wherein the weights and delays are jointly
2 optimized as a solution to a quadratic optimization problem to
3 approximately minimize a deviation from the spectral mask.
- 1 15. The method of claim 1 further comprising:
2 selecting the set of basis pulses from a candidate set of basic pulses by
3 greedy addition to optimizing the delays.
- 1 16. The method of claim 1 further comprising:
2 selecting the set of basis pulses from a candidate set of basic pulses by
3 greedy removal to optimizing the delays.
- 1 17. The method of claim 1 further comprising:
2 orthogonalizing and normalizing the set of basis pulses; and
3 applying a branch and bound procedure to the set of orthogonalized
4 and normalized basis pulses to optimize the delays.
- 1 18. The method of claim 17 wherein bounds of the branch and bound
2 procedure are determined by Cauchy's interlacing theorem of eigenvalues
3 for symmetry matrices.
- 1 19. The method of claim 17 wherein the branch and bound procedure further
2 comprises:

3 constructing an enumeration tree with an increasing number of zeros
4 in vectors representing the delays.

1 20. The method of claim 1 wherein the basis pulses are selected off-line
2 from a set of basis pulses by a combinatorial optimization using training
3 spectral masks.

1 21. A system for shaping a spectrum of an impulse radio signal, comprising:
2 means for generating a set of basis pulses at a plurality of frequencies
3 and a plurality of random delays
4 a set of filters configured to weight the set of basis pulses by weights;
5 a set of delay lines configured to delay the set of basis pulses by
6 delays; and
7 an adder configured to combine linearly the weighted and delayed
8 basis pulses to conform the spectrum to a spectral mask.

1 22. The system of claim 21 further comprising:
2 a set of oscillators configured to shift frequencies of the weighted and
3 delayed basis pulses before the combining.

Abstract of the Disclosure

A method and system shapes a spectrum of an impulse radio signal, such as an UWB signal. First, basis pulses at various frequencies and pseudo-random delays are generated. The generated set of basis pulses are then weighted and delayed, and combined linearly to conform the spectrum of the transmitted basis pulses to a spectral mask. The spectral mask can be predetermined, or the conforming can be adaptive. Furthermore, the basis pulses can be frequency-shifted before the combining.